

Supported Infrastructure Devices

AirWave provides a range of features to manage network infrastructure devices from Aruba Networks and other vendors. This document describes the supported product families, software versions, and feature set for the following product sets:

- "Aruba Devices" on page 1
- "Hewlett Packard Enterprise Devices" on page 6
- "Other Third-Party Vendor Devices" on page 10
 - "Cisco® Devices" on page 10
 - "Juniper® Devices" on page 13
 - "Meru® Devices" on page 14
 - "Motorola® Devices" on page 15
 - "Other Third-Party Devices with Monitoring Support" on page 16
- "Other Switches" on page 17

Aruba Devices

This release of AirWave supports management of global configuration profiles or settings, monitoring, and software upgrades on the Aruba devices and software described in the following sections.

ArubaOS

AirWave supports all Aruba controllers and most access points (APs) that are running the following versions:

- 6.4.4.0
- 6.5.0.0, 6.5.1.0, 6.5.2.0, 6.5.3.0, and 6.5.4.0
- 8.0.0.0 and 8.0.1.0
- 8.1.0.0, 8.1.0.2, and 8.1.0.3
- 8.2.0.0 and 8.2.1.0
- 8.3.0.0, 8.3.0.1, 8.3.0.2, and 8.3.0.3
- 8.4.0.0, 8.4.0.1, and 8.4.0.2
- 8.5.0.0

Table 1 lists the supported devices and the tested ArubaOS firmware versions.

Table 1: *Supported Devices*

Device	Validated up to
AP-555	8.5.0.0
AP-534 and AP-535	8.5.0.0
AP-514 and AP-515	8.4.0.0

Table 1: Supported Devices (Continued)

Device	Validated up to
AP-387	8.4.0.0
AP-374, AP-375, and AP-377	8.3.0.0
AP-365 and AP-367	6.5.2.0
AP-344 and AP-345 with Dual 5-GHz Mode	8.3.0.0
AP-334 and AP-335	6.5.1.0
AP-324 and AP-325	6.5.1.0
AP-318	8.3.0.0
AP-314 and AP-315	6.5.0.0
AP-304 and AP-305	6.5.1.0
AP-303	8.3.0.0
AP-303H and AP-303HR	6.5.2.0
AP303P	8.3.0.0
AP-277	6.5.0.0
AP-274 and AP-275	6.5.0.0
AP-228	6.5.0.0
AP-224 and AP-225	6.5.0.0
AP-214 and AP-215	6.5.0.0
AP-207	6.5.1.0
AP-205H	6.5.0.0
AP-204 and AP-205	6.5.0.0
AP-203H	6.5.2.0
AP203-R and AP-203RP	6.5.2.0
AP-175	6.5.0.0
AP-134 and AP-135	6.5.0.0
AP-124 and AP-125	6.5.0.0
AP-114 and AP-115	6.5.0.0

Table 1: Supported Devices (Continued)

Device	Validated up to
AP-104 and AP-105	6.5.0.0
AP-103	6.5.0.0
AP-103H	6.5.0.0
AP-92 and AP-93	6.5.0.0
AP-93H	6.5.0.0
AP-68	6.5.0.0
3000 Series Controller	6.4.4.0
7005 Controller	6.5.0.0
7010 Controller	6.5.0.0
7024 Controller	6.5.0.0
7030 Controller	6.5.0.0
7200 Series Controller	6.5.0.0
7280 Controller	6.5.0.0

AirWave also supports Aruba unified APs, which are APs factory-installed with 6.5.2.0 or a later. A unified AP can be configured to operate as either a campus AP or a remote AP when that device is first provisioned.

For more information on unified APs, refer to the *6.5.2 Release Notes*.

For the complete list of products that have reached the end of life milestone and are not supported, refer to <http://www.arubanetworks.com/support-services/end-of-life/https://businessportal2.alcatel-lucent.com>.

Aruba Instant

Table 2 lists the Instant firmware versions and functions supported by AirWave. AirWave also supports the Aruba RAP-100 Series and RAP-3 Series remote access points.

Table 2: Supported Aruba Instant Firmware Versions and Functions

Instant Version	Support for	
	Template Config	Instant GUI Config
Instant 8.5.0.0	AirWave 8.2.9	AirWave 8.2.9
Instant 8.4.0.1	AirWave 8.2.8.2	AirWave 8.2.8.2
Instant 8.4.0.0	AirWave 8.2.8.1	AirWave 8.2.8.1
Instant 8.3.0.0	AirWave 8.2.7.1	AirWave 8.2.7.1

Table 2: Supported Aruba Instant Firmware Versions and Functions (Continued)

Instant Version	Support for	
	Template Config	Instant GUI Config
Instant 8.3.0.0	AirWave 8.2.6.1	AirWave 8.2.6.1
Instant 6.5.4.0	AirWave 8.2.5.1	AirWave 8.2.5.1
Instant 6.5.4.0	AirWave 8.2.5	AirWave 8.2.5
Instant 6.5.3.0	AirWave 8.2.4.1	AirWave 8.2.4.1
Instant 6.5.2.0	AirWave 8.2.4	AirWave 8.2.4
Instant 4.3.1.0	AirWave 8.2.3.1	AirWave 8.2.3.1
Instant 4.3.0.0	AirWave 8.2.3	AirWave 8.2.3
Instant 4.2.4.0	AirWave 8.2.1	AirWave 8.2.2
Instant 4.2.3.0	AirWave 8.2.0	AirWave 8.2.2



Starting with 6.4.3.x-4.2, Instant software does not support IAP-92 and IAP-93.

Aruba Switches

AirWave supports monitoring, template configuration, and firmware changes on the Aruba switches listed in [Table 3](#). On these switches, you can set up device-specific triggers and alerts and designate them as trap receivers. If you want to see the SNMP traps, go to the **System > Syslog & Traps** page.

In addition, you can push a complete configuration profile using templates to Aruba switches that have a factory-default configuration, or you can send configuration jobs using switch CLI commands and snippets to switches in a device group.



In VisualRF, these Aruba switches appear in the VisualRF product catalog. However, their utilization values will be 0 because AirWave does not get utilization values for these devices.

Table 3: Supported Aruba Switches

Device	Monitoring	Configuration	Firmware Upgrade	Validated Firmware Version
Aruba 2530YA	Yes	Yes	Yes	YA.16.08
Aruba 2530YB	Yes	Yes	Yes	YB.16.08
Aruba 2540	Yes	Yes	Yes	YC.16.08
Aruba 2620	Yes	Yes	Yes	RA.16.04.0016
Aruba 2920	Yes	Yes	Yes	WB.16.08

Table 3: Supported Aruba Switches (Continued)

Device	Monitoring	Configuration	Firmware Upgrade	Validated Firmware Version
Aruba 2930F	Yes	Yes	Yes	WC.16.08
Aruba 2930M	Yes	Yes	Yes	WC.16.08
Aruba 3800	Yes	Yes	Yes	KA.16.08
Aruba 3810	Yes	Yes	Yes	KB.16.08
Aruba 5400R	Yes	Yes	Yes	KB.16.08
Aruba 5406zl	Yes	No	No	K.15.16.08
Aruba 5412zl	Yes	No	No	K.15.16.0021
Aruba 8320	Yes	No	No	10.02
Aruba 8325	Yes	No	No	10.02
Aruba 8400	Yes	No	No	10.02

Aruba Mobility Master Appliances

AirWave supports the following devices running ArubaOS 8.0.0.0 and later:

- Mobility Master Hardware Appliance MM-HW-1K, MM-HW-5K, and MM-HW-10K
- Mobility Master Virtual Appliance MM-VA

Aruba Mobility Access Switches

AirWave supports profile configuration, monitoring, and software upgrades on the Aruba Mobility Access Switches. In addition to the port statistics supported for most Ethernet switches with the supported firmware described below, AirWave also tracks the activity of authenticated wired clients on Aruba switches.

Table 4: Supported Aruba Mobility Access Switches

Device	Validated up to
S1500	7.4.0.0
S2500	7.4.0.0
S3500	7.4.0.0

Aruba AirMesh

Aruba AirMesh outdoor products running MeshOS 4.2 are supported for monitoring and software upgrades.

Table 5: Supported Aruba MeshOS Devices

Device	Validated up to
MSR1200	MeshOS 4.2
MSR2000	MeshOS 4.2
MSR4000	MeshOS 4.2
MST200	MeshOS 4.2

Hewlett Packard Enterprise Devices

The firmware versions for the HPE devices listed [Table 6](#) represent the latest firmware version verified as fully supported by AirWave 8.2.9. The devices in [Table 6](#) are available within the VisualRF product catalog and can be selected when setting up device-specific triggers and alerts. In addition, these devices can be set up as trap receivers, and the SNMP traps can be seen on the **System > Syslog & Traps** page.



AirWave does not support MSM APs running in autonomous mode.



Informal testing shows that AirWave supports some devices running more recent versions of firmware, but full support for these later versions is not guaranteed.

For more information on configuring and managing and HPE switches via AirWave, refer to the *AirWave Switch Configuration Guide*.

Table 6: HPE Device Support

Model	FirmWare Validated Up To
MSM310 and MSM310R	6.5.1.0
MSM313 and MSM313R	6.5.1.0
MSM317	6.5.1.0
MSM318	6.5.1.0
MSM320 and MSM320R	6.5.1.0
MSM323 and MSM323R	6.5.1.0
MSM325	6.5.1.0
MSM335	6.5.1.0
MSM410	6.5.1.0
MSM417*	6.5.1.0
MSM422	6.5.1.0
MSM425*	6.5.1.0

Table 6: HPE Device Support (Continued)

Model	FirmWare Validated Up To
MSM430	6.5.1.0
MSM460	6.5.1.0
MSM466 and 466R	6.5.1.0
MSM525*	6.5.1.0
MSM527*	6.5.1.0
MSM560*	6.5.1.0
MSM710 Controller	6.5.1.0
MSM720 Controller	6.5.1.0
MSM730 Controller	6.5.1.0
MSM750 Controller	6.5.1.0
MSM760 Controller	6.5.1.0
MSM765 Controller	6.5.1.0
ProCurve 420	2.0.38 - 2.2.5
ProCurve 530	WA.01.16-WA.02.19
ProCurve 2626-PWR	H.10.35 (ROM H.08.02)
830 Unified Wired-WLAN Switch*	5.20.109 (Release 2607P39)
850 Unified Wired-WLAN Switch*	5.20.109 (Release 2607P39)
870 Unified Wired-WLAN Switch*	5.20.109 (Release 2607P39)
HPE WESM controllers & APs xl	WS.01.05 – WS.02.19
HPE WESM controllers & APs zl	WT.01.03 – WT.01.28
HPE 1405 Switch Series	**
HPE 1420 Switch Series	**
HPE 1620 Switch Series	**
HPE 1820 Switch Series	**
HPE 1850 Switch Series	**
HPE 1910 Switch Series	**

Table 6: HPE Device Support (Continued)

Model	FirmWare Validated Up To
HPE 1920 Switch Series	**
HPE 1950 Switch Series	2220P02 (Comware 7)
HPE 3100 Switch Series	2220P02 (Comware 7)
HPE 3600 Switch Series	2220P02 (Comware 7)
HPE 5120 Switch Series	2220P02 (Comware 7)
HPE 5130 Switch Series	2220P02 (Comware 7)
HPE 5500 Switch Series	2220P02 (Comware 7)
HPE 5510 HI Switch Series	**
HPE 5700 Switch Series	**
HPE 5800 Switch Series	**
HPE 5820 Switch Series	1810P13 (Comware 7)
HPE 5900 Switch Series	2220P02 (Comware 7)
HPE 7500 Switch Series	2220P02 (Comware 7)
HPE 7900 Switch Series	**
HPE 10500 Switch Series	2220P02 (Comware 7)
HPE 12900E Switch Series	**
* Not supported in VisualRF. **Limited testing done. Contact Technical Support for help with any issues.	

High Availability Support

AirWave 8.2 introduces support for pairs of HP Unified Wired-WLAN (UWW) devices operating in HA mode. AirWave monitors the status of each controller. After AirWave detects that a failover occurred and the APs failed over to the backup controller, AirWave displays the current status of the APs.

Monitoring Support

AirWave provides monitoring through SNMP polling with the OIDs listed in the following table.

Table 7: Monitoring Support

Model	SNMP Object ID	SysOID
HPE 7502 Switch	1.3.6.1.4.1.25506.11.1.1	.1.3.6.1.4.1.25506.11.1.269
HPE 7503S Switch	1.3.6.1.4.1.25506.11.1.2	.1.3.6.1.4.1.25506.11.1.268
HPE 7503 Switch	1.3.6.1.4.1.25506.11.1.3	.1.3.6.1.4.1.25506.11.1.270

Table 7: Monitoring Support (Continued)

Model	SNMP Object ID	SysOID
HPE 7506 Switch	1.3.6.1.4.1.25506.11.1.4	.1.3.6.1.4.1.25506.11.1.267
HPE 7506-V Switch	1.3.6.1.4.1.25506.11.1.5	.1.3.6.1.4.1.25506.11.1.264
HPE 7510 Switch	1.3.6.1.4.1.25506.11.1.6	.1.3.6.1.4.1.25506.11.1.271
HPE 9505 Switch	1.3.6.1.4.1.25506.11.1.39	.1.3.6.1.4.1.25506.11.1.266
HPE 9508-V Switch	1.3.6.1.4.1.25506.11.1.40	.1.3.6.1.4.1.25506.11.1.265
HPE 9508 Switch	1.3.6.1.4.1.25506.11.1.41	.1.3.6.1.4.1.25506.11.1.272
HPE 9512 Switch	1.3.6.1.4.1.25506.11.1.43	.1.3.6.1.4.1.25506.11.1.144
HPE 10504 Switch	1.3.6.1.4.1.25506.11.1.86	.1.3.6.1.4.1.25506.11.1.229
HPE 10508 Switch	1.3.6.1.4.1.25506.11.1.87	.1.3.6.1.4.1.25506.11.1.230
HPE 10508-V Switch	1.3.6.1.4.1.25506.11.1.88	.1.3.6.1.4.1.25506.11.1.145
HPE 10512 Switch	1.3.6.1.4.1.25506.11.1.89	.1.3.6.1.4.1.25506.11.1.231
HPE Switches	*.25506.11.1 *	.1.3.6.1.4.1.25506.11.1.232
HPE Routers	*.25506.11.2 *	NA
HPE Wireless	*.25506.11.3*	NA
HPE Security	*.25506.11.4 *	NA
HPE (3Com) S7503E-M	1.3.6.1.4.1.25506.1.1504	NA
HPE (3Com) S7502	1.3.6.1.4.1.25506.1.52	NA
HPE (3Com) S7502E	1.3.6.1.4.1.25506.1.207	NA
HPE (3Com) S7502ESX	1.3.6.1.4.1.25506.1.1309	NA
HPE (3Com) S7503	1.3.6.1.4.1.25506.1.53	NA
HPE (3Com) S7503E	1.3.6.1.4.1.25506.1.208	NA
HPE (3Com) S7503E-S	1.3.6.1.4.1.25506.1.370	NA
HPE (3Com) S7503X	1.3.6.1.4.1.25506.1.1560	NA
HPE (3Com) S7503X-G	1.3.6.1.4.1.25506.1.1836	NA
HPE (3Com) S7504EXS	1.3.6.1.4.1.25506.1.1308	NA
HPE (3Com) S7506	1.3.6.1.4.1.25506.1.54	NA

Table 7: Monitoring Support (Continued)

Model	SNMP Object ID	SysOID
HPE (3Com) S7506E	1.3.6.1.4.1.25506.1.209	NA
HPE (3Com) S7506E-S	1.3.6.1.4.1.25506.1.469	NA
HPE (3Com) S7506E-V	1.3.6.1.4.1.25506.1.210	NA
HPE (3Com) S7506E-X	1.3.6.1.4.1.25506.1.1306	NA
HPE (3Com) S7506X-G	1.3.6.1.4.1.25506.1.1837	NA
HPE (3Com) S7506X-R	1.3.6.1.4.1.25506.1.55	NA
HPE (3Com) S7508E-X	1.3.6.1.4.1.25506.1.636	NA
HPE (3Com) S7510E	1.3.6.1.4.1.25506.1.159	NA
HPE (3Com) S7510E-X	1.3.6.1.4.1.25506.1.1307	NA
HPE (3Com) S7510X	1.3.6.1.4.1.25506.1.1562	NA

HPE ProCurve

HPE ProCurve switches have the following additional support through AirWave:

- Automated discovery through SNMP
- Model & software version identification

Other Third-Party Vendor Devices

AirWave supports the following monitoring features for other third party devices:

- User monitoring data such as connection time, user name, SSID, and bandwidth
- Network monitoring data, including real-time and historical bandwidth and user count metrics
- Rogue detection and classification using AirWavecustomizable rules
- VisualRF heatmaps and user/rogue location
- Reports
- Triggers and alerts

In some cases, you can do basic configuration and firmware upgrades, as well as discover third-party controller and APs.

Cisco® Devices

AirWave supports Cisco devices that are running the latest verified firmware versions and have not reached the end of life milestone. Informal testing shows that AirWave supports devices running more recent versions of firmware, but full support for these later versions is not validated.

Cisco Autonomous Access Points

AirWave provides monitoring, management, and software upgrade support for the devices listed in [Table 8](#).

Table 8: Supported Cisco Autonomous Access Points

Model	Validated up to
350 Series Access Points	IOS 12.3(11)JA and IOS 12.4(21a)JA1
702 Series Access Points	IOS: 15.3(3)JD
801 Series Integrated Access Points	IOS 12.4(25d)JA2 and IOS 15.(22)JB
819 Series Integrated Service Routers	IOS 15.6.3M5
860 Series Access Points	IOS 12.4(15)XZ, 12.4(20)T
881 Series Access Points	IOS 12.4(21a)JA1
881W Series Access Points	IOS 12.4(21a)JA1 and IOS 15.0(1)M7
881GW Series Access Points	IOS 12.4(21a)JA1 and IOS 15.1(4)M3
891 Series Access Points	IOS 12.4(21a)JA1 and IOS 15.0(1)M7
1040 Series Access Points	IOS 12.4(21a)JA1
1100 Series Access Points	IOS 12.4(21a)JA1
1110 Series Access Points	IOS 12.4(21a)JA1 and IOS 12.3(11)JA
1130 Series Access Points	IOS 12.4(21a)JA1
1140 Series Access Points	IOS 12.4(21a)JA1 and IOS 12.3(11)JA
1200 Series Access Points	IOS 12.4(21a)JA1 and IOS 12.3(11)JA
1210 Series Access Points	IOS 12.4(21a)JA1
1230 Series Access Points	IOS 12.4(21a)JA1
1240 Series Access Points	IOS 12.4(21a)JA1
1250 Series Access Points	IOS 12.4(21a)JA1
1260 Series Access Points	IOS 12.4(21a)JA1
1300/1400 Series Bridges	IOS 12.4(21a)JA1
1700 Series Access Points	IOS 10.2.111.0 (IOS: 15.3(3)JN3)
1941W Series Access Points	IOS 15.2(3)T
2700 Series Access Points	IOS 10.2.111.0 (IOS: 15.3(3)JN3)

Cisco Wireless Controllers and Access Points

AirWave supports monitoring, RAPIDS, device discovery, and VisualRF for these devices, as well as configuration, firmware identification, AMP upgrade, and client monitoring-diagnostics for wireless controllers.

Table 9 lists the Cisco wireless controllers and access point platforms that are supported in this release.

Table 9: Supported Cisco Wireless Controllers and Access Points

Model	Validated up to
1040 Series Access Points	8.3.102.0
1130 Series Access Points	7.6.110.0 (Bootloader: 7.0.116.0)
1140 Series Access Points	8.3.102.0
1200 Series Access Points	8.3.102.0
1550 Series Access Points	8.3.102.0
1600 Series Access Points	8.3.102.0
1700 Series Access Points	8.3.102.0
1800 Series Access Points	8.3.102.0
2600 Series Access Points	8.3.102.0
2700 Series Access Points	8.3.102.0
2802 Series Access Points	8.5.110.0
3500 Series Access Points	8.3.102.0
3600 Series Access Points	8.3.102.0
3700 Series Access Points	8.3.102.0
3800 Series Access Points	8.3.102.0
2100 Series Wireless Controllers	7.0.235.0 (Bootloader: 7.0.235.0)
2500 Series Wireless Controllers	8.3.102.0
4400 Series Wireless Controllers	7.0.235.0 (Bootloader: 7.0.235.0)
5500 Series Wireless Controllers	8.5.110.0
5760 Wireless Controllers	3.2.0
Flex 7500 Controllers	8.3.102.0
8510 Controllers	8.5.110.0



Cisco Mobility Services Engine and 500 Series Access Points are not supported.

Cisco Switches

AirWave supports automated discovery through SNMP, model and firmware version identification, and displays CDP neighbor information and extended port error statistics for the Cisco switches listed in [Table 10](#).

Table 10: Supported Cisco Switches

Model	Validated up to
Catalyst 9400 Series Switches	16.06.03
Catalyst 2900 Series Switches (monitoring only)	15.0(2)SE11
Catalyst 3650 Series Switches	03.06.06E
Catalyst 3750 Series Switches	12.2(55)SE11
Catalyst 3850 Series Switches	03.06.06E
Industrial Ethernet 4000 Series Switches	15.2(4)EA5
Aironet 4800 Series Bridges (pre-VxWorks, monitoring only)	8.65_2

AirWave doesn't update the upstream device information for access points connected to Cisco switches when Cisco switches are polled when using SNMPv3. Cisco has restricted access to the BRIDGE-MIB when using SNMPv3. When you access a Cisco switch using SNMPv3, APs connected to that switch may not be able to show upstream device info. As a workaround to this issue, add SNMPv3 bridge commands to the Cisco switches in order to expose VLAN values for the MIB polled by UDT. If there are devices on a switch, add the following command for each VLAN-#:

```
snmp-server group <GroupName> v3 priv context
```

You may need to append views to the command, as follows:

```
snmp-server group <GroupName> v3 priv context <VLAN-#> read <ViewName>
```

Use the **match prefix** parameter to all existing VLANs:

- `snmp-server group <GroupName> v3 priv context vlan- match prefix`
- `snmp-server group <GroupName> v3 priv context vlan- match prefix access`

Juniper® Devices

The following Juniper controllers and APs are supported for monitoring, configuration, and software upgrades.



The firmware versions listed in the table below represents the latest firmware version verified as fully supported by AirWave 8.2.9. Informal testing shows that AirWave supports devices running more recent versions of firmware, but full support for these later versions is not guaranteed.

Table 11: Supported Juniper Access Points and Wireless LAN Controllers

Model	Validated up to
WLA321 Access Points	9.1.0.6.0
WLA322 Access Points	9.1.0.6.0
WLA522 Access Points	9.1.0.6.0
WLA532 Access Points	9.1.0.6.0
WLA632 Access Points	9.1.0.6.0

Table 11: Supported Juniper Access Points and Wireless LAN Controllers (Continued)

Model	Validated up to
WLC100 Wireless LAN Controllers	9.1.0.6.0
WLC2 Wireless LAN Controllers	9.1.0.6.0
WLC2800 Wireless LAN Controllers	9.1.0.6.0
WLC8 Wireless LAN Controllers	9.1.0.6.0
WLC800 Wireless LAN Controllers	9.1.0.6.0
WLC880 Wireless LAN Controllers	9.1.0.6.0
WLC JunosV Wireless LAN Controllers	9.1.0.6.0
Juniper Switch	12.3R6.6

Juniper®

Juniper switches have the following additional support through AirWave:

- Automated discovery through SNMP
- Model & software version identification
- Rogue AP detection is supported using the Q-BRIDGE MIB

Meru® Devices

The following Meru controllers and APs are now supported in VisualRF.



The firmware versions listed in the table below represents the latest firmware version verified as fully supported by AirWave 8.2.9. Informal testing shows that AirWave supports devices running more recent versions of firmware, but full support for these later versions is not guaranteed.

Table 12: Meru Device Support

Model	Validated up to
AP302	6.1.1-25
AP320i	6.1.1-25
AP332i	6.1.1-25
AP433i	6.1.1-25
AP433is	6.1.1-25
AP822e	6.1.1-25
AP822i	6.1.1-25
AP832e	6.1.1-25
AP832i	6.1.1-25

Table 12: Meru Device Support (Continued)

Model	Validated up to
RS4000	6.1.1-25
MC1000*	3.6.1-49
MC1550	6.1.1-25
MC3000*	3.6.1-49
MC3200	6.1.1-25
MC4200	6.1.1-25
MC5000*	3.6.1-49
*This version of AirWave supports monitoring for these devices.	



VisualRF support for the for the AP433i, AP433e, AP433is, AP822i, and AP822e is not included in this release of AirWave.

Motorola® Devices

The following Motorola (formerly Symbol) controllers and autonomous APs are supported for monitoring, configuration, and software upgrades.



The firmware versions listed in the table below represents the latest firmware version verified as fully supported by AirWave 8.2.9. Informal testing shows that AirWave supports devices running more recent versions of firmware, but full support for these later versions is not guaranteed.

Table 13: Motorola Autonomous AP, Wireless LAN Controller, and AP Support

Model	Validated up to
AP621	5.4.2.0-030R
AP622	5.4.2.0-030R
AP650	5.4.2.0-030R
AP5131	5.4.2.0-030R
AP5181	5.4.2.0-030R
AP6521*	5.4.2.0-030R
AP6522*	5.4.2.0-030R
AP6532*	5.7.0.0-057R
AP7131	5.4.2.0-030R
AP7161	5.4.2.0-030R

Table 13: Motorola Autonomous AP, Wireless LAN Controller, and AP Support (Continued)

Model	Validated up to
AP7532	5.8.1.0-012R
NX9600	5.8.6.0-011R
RFS4000	5.4.2.0-030R
RFS6000	5.4.2.0-030R
RFS7000	5.4.2.0-030R
WS2000	2.4.5
WS5100	3.3.4
Wing5 RFS controllers	5.4.2.0-030R
* These AP and controller models may require adjustments to the AirWave SNMP timeouts to compensate for known SNMP issues on these devices.	

Other Third-Party Devices with Monitoring Support

This version of AirWave supports monitoring for a variety of devices with software versions listed in the table below.



The firmware versions listed in the table below represents the latest firmware version verified as fully supported by AirWave 8.2.9. Informal testing shows that AirWave supports devices running more recent versions of firmware, but full support for these later versions is not guaranteed.

Table 14: Other Supported Devices

Device	Validated up to
BelAir 200	main.2005.03.29
Brocade ICX switches	08.0.20T211 and 08.0.30aT213
Ericsson APM-210 Access Point Modules	6.4.4.0-sp
Proxim AP-600/700	2.0 – 4.0.2
Proxim AP 2000/4000	2.0 – 4.0.2
Proxim Tsunami MP.11 QB 954-x, 2454-x, 4954-x, 5054-x	2.3.0 – 4.0.0
Siemens SCALANCE W1750D	6.5.0.0 - 4.3.0
Siemens SCALANCE XC208G switches	
Siemens SCALANCE XR500 switches	
Siemens SCALANCE XR400 plug-in transceiver	

Table 14: *Other Supported Devices (Continued)*

Device	Validated up to
Siemens SCALANCE XR300 switches	
Symbol 3021	04.01-23 – 04.02-19
Symbol 4121 and 4131	3.51-20 – 3.95-04
Symbol 5131/5181	1.1.0.0.045R – 2.5.0.0
Trapeze MXR-2, MXR-8, MXR-20, MXR-2xx, MX-400, MP-3x2, and MP-422	5.0.12.2 – 7.0.5.6
Tropos 3/4/5210/5320/9422/9532	5.1.4.7 – 6.6.1.3

Other Switches

Some switches have additional support in AirWave:

Alcatel-Lucent OmniSwitch™ (6250 and 6450)

- Automated discovery through SNMP
- Model & software version identification
- Stack information
- Firmware version 6.6.1.859.R01

Brocade

- Automated discovery through SNMP
- Model & software version identification
- Firmware version 08.0.20T211 and 08.0.30aT213
- Stacking

Force10

- Model & software version identification
- Firmware version 8.4.2.9

Contacting Support

Main Site	arubanetworks.com
Support Site	support.arubanetworks.com
Airheads Social Forums and Knowledge Base	community.arubanetworks.com
North American Telephone	1-800-943-4526 (Toll Free) 1-408-754-1200
International Telephone	arubanetworks.com/support-services/contact-support/
Software Licensing Site	hpe.com/networking/support
End-of-life Information	arubanetworks.com/support-services/end-of-life/
Security Incident Response Team (SIRT)	Site: arubanetworks.com/support-services/security-bulletins/ Email: aruba-sirt@hpe.com



www.arubanetworks.com
6280 America Center Drive
San Jose, CA 95002

Phone: 1-800-WIFI-LAN (+800-943-4526)
Fax 408.752.0626

© Copyright 2019 Hewlett Packard Enterprise Development LP