

AirWave provides a range of features to manage network infrastructure devices from Aruba Networks and other vendors. This document describes the supported product families, software versions, and feature set for the following product sets:

- "Wireless LAN APs and Controllers" on page 1
 - Aruba
 - Cisco
 - Motorola
 - HP
- "Wired Ethernet Switches" on page 3
 - Aruba Mobility Access Switches
 - Other switches
- "Other Devices with Monitoring Support" on page 4

Wireless LAN APs and Controllers

Aruba

AirWave supports all Aruba controllers and most access points that have not reached the End of Support milestone. The AP-80M series of access points is not supported by AirWave.

Controllers running ArubaOS 6.1.3.x, 6.1.4.x FIPS, and all prior versions that have not reached the End of Support milestone are supported by this version of AirWave, including the management of global configuration profiles and software upgrades.

Aruba Instant APs running software versions 6.1.3.1-3.0.0.x and prior are also supported, including the management of configuration settings and software upgrades.

Aruba Mobility Controller 651 running 5.0.4.9 and prior versions are supported.

Aruba AirMesh outdoor products running MeshOS 4.2 are supported for monitoring and for software upgrades.

Refer to <http://www.arubanetworks.com/support-services/end-of-life-products> for the complete list of end-of-life products.

Cisco

Autonomous APs running IOS

The following IOS AP product families are supported for monitoring, configuration, and software upgrades:

Validated up to IOS 12.3(11)JA:

- 350 series
- 1100, 1130, 1140 series

Validated up to IOS 12.4(21a)JA1:

- 350, 1040, 1100, 1130, 1140, 1200, 1210, 1230, 1240, 1250, 1260 series
- 1300/1400 series bridges
- 871W (no software upgrade support), 881, 881GWAP, 891 series

Validated up to IOS 12.4(23c)JA2:

- 1941 series AP

Validated up to IOS 15.0(1)M7:

- 891W, 881W series

Validated up to IOS 15.1(4)M3:

- 881GW series

Validated up to IOS 15.2(3)T:

- 1941W series

Validated up to IOS 15.2(3)T2:

- 880, 890, 1900 series

Support is also available for the following products:

- 860 series

Wireless LAN Controllers

The following controllers and thin APs are supported for monitoring, configuration, and software upgrades:

Validated up to software version 7.2

- Standalone 2000, 2100, 2500 (bootloader 1.0.16), 4400, and 5500 series controllers
- 1000, 1040, 1130, 1140, 1200, 1230, 1340, 1250, 1260, 3500 series APs
- Cisco Catalyst 3750G Integrated WLC
- WiSM/WiSM2

Validated up to software version 7.2.110.0

- 600 and 3600 series APs

Validated up to software version 7.3.101.0

- 7500 WLC Flex Controller

Support is not available for the following products:

- Mobility Services Engine
- 500 series APs

Support for legacy Cisco devices is described at the end of the document.

Motorola

The following Motorola (formerly Symbol) controllers and autonomous APs are supported for monitoring, configuration, and software upgrades up to software version 4.3.3:

Controllers

- RFS4000/6000/7000
- WS2000 (validated up to 2.4.5)
- WS5100 (validated up to 3.3.4)

Autonomous APs

- 5131
- 5181
- 7131

Support for legacy Motorola/Symbol devices is described at the end of the document.



Motorola 5.x software is not supported by AirWave.

HP

The following HP devices are supported for monitoring and software upgrades.

Validated up to software version 5.7.1.0-12275:

- HP MSM430
- HP MSM460
- HP MSM466
- HP MSM710 (controller)
- HP MSM720 (controller)

These devices are available within the VisualRF product catalog and can be selected when setting up device-specific triggers and alerts. In addition, these devices can be set up as trap receivers, and the SNMP traps can be seen on the **System > Syslog & Traps** page.

Support for additional HP devices is described at the end of the document.



In VisualRF, the utilization value for HP devices will be 0 because AirWave does not get utilization values for these devices.

Wired Ethernet Switches

Any standalone Ethernet access switch that supports the standard SNMP MIB-II objects for wired switches can be monitored by AirWave.

AirWave will collect the uptime and name/location/contact information for switches (or any device that supports SNMP). For port information, AirWave relies on the IF-MIB to collect byte counts.

MAC addresses are collected from the BRIDGE MIB and RFC1213 MIB (ARP table) in order to determine AP port assignments and identify possible rogue devices on the network.

Aruba S3500 Mobility Access Switches

The Aruba S3500 series of Mobility Access Switches are supported for monitoring and software upgrades. This version of AirWave also introduces support for configuration of a subset of the available configuration profiles.

In addition to the port statistics supported for most Ethernet switches described below, AirWave also tracks the activity of authenticated wired clients on Aruba switches.

Validated up to 7.0.2.0:

- Standalone switches (no stacking switches)

Validated up to 7.1.0.0:

- Stacked switches

Validated up to 7.1.3.2:

- Stacked switches

Other Switches

Some switches have additional support in AirWave:

Cisco

- Automated discovery through SNMP
- Model & software version identification
- CDP neighbor information and extended port error stats
- 3750 stack information

Juniper

- Automated discovery through SNMP
- Model & software version identification
- Rogue AP detection is supported using the Q-BRIDGE MIB

HP ProCurve

- Automated discovery through SNMP
- Model & software version identification

Alcatel-Lucent OmniSwitch (6250 and 6450)

- Automated discovery through SNMP
- Model & software version identification
- Stack information
- Firmware version 6.6.1.859.R01

Other Devices with Monitoring Support

This version of AirWave supports monitoring for a variety of devices with software versions listed here:

Table 1: *Other Supported Devices*

Device	Supported Firmware
BelAir 200	main.2005.03.29
Cisco 4800 (Pre-VxWorks)	8.65.2
HP MSM7xx and APs	5.5.3.0-01
HP ProCurve 420	2.0.38 - 2.2.5
HP ProCurve 530	WA.01.16-WA.02.19
HP 5406 zl Switch	K.12.43 (ROM:K.12.12)
HP WESM controllers & APs <ul style="list-style-type: none">● xl● zl	<ul style="list-style-type: none">● WS.01.05 - WS.02.19● WT.01.03 - WT.01.28
Juniper Switch	10.4R1.9
Meru MC1000, MC3000, MC5000	3.3-118 - 3.6.1-49
Proxim AP-600/700 Proxim AP 2000/4000	2.0 - 4.0.2

Device	Supported Firmware
Proxim Tsunami MP.11 QB 954-x, 2454-x, 4954-x, 5054-x	2.3.0 - 4.0.0
Symbol 3021	04.01-23 - 04.02-19
Symbol 4121/4131	3.51-20 - 3.95-04
Symbol 5131/5181	1.1.0.0.045R - 2.5.0.0
Trapeze MXR-2, MXR-8, MXR-20, MXR-2xx, MX-400, MP-3x2, MP-422	5.0.12.2 - 7.0.5.6
Tropos 3/4/5210/5320/9422/9532	5.1.4.7 - 6.6.1.3

